









ENTERPRISE ANTENNAS

Series	5G  <i>Akita</i>	5G  <i>Labrador</i>	 <i>Weimaraner</i>	 <i>Great Dane</i>	5G  <i>Husky</i>	5G  <i>Bulldog</i>	
Configurable up to:	4 CELL, 1 GPS	2 CELL	2 WiFi	2 CELL	4 CELL, 4 WI-FI, GPS	8 CELL, 4 WI-FI, GPS	
Antenna Configuration Options	4:1, 5:1	2:1	2:1	2:1	4:1, 5:1, 7:1, 8:1, 9:1, 11:1	4:1, 8:1, 12:1, 13:1	
Compatible Router Configurations	4 Cellular	2 Cellular	2 Wi-Fi	2 Cellular	4 Cellular	4 Cellular	
	4 Cellular, 1 GPS				4 Cellular, 1 GPS	4 Cellular, 4 Wi-Fi	
					4 Cellular, 2 Wi-Fi, 1 GPS	4 Cellular, 2 Wi-Fi, 1 GPS	8 Cellular
						4 Cellular, 2 Wi-Fi, 1 Bluetooth, 1 GPS	
4 Cellular, 4 Wi-Fi, 1 GPS	8 Cellular, 4 Wi-Fi						
Cellular Frequency Range	600 MHz - 6 GHz	600 MHz - 6 GHz	Wi-Fi Only	600 MHz - 6 GHz	600 MHz - 6 GHz	600 MHz - 6 GHz	
North American Bands Supported	B2, B4, B5, B7, B12, B13, B14, B17, B24, B25, B26, B29, B30, B41, B46, B48, B66, B70, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	N/A	Coming Soon	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	
EMEA Bands Supported	B1, B3, B7, B8, B20, B28, B32, B42, B43, B46 n1, n3, n8, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n8, n77, n78	N/A	Coming Soon	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78	
Pattern	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	
IP Rating	IP54	IP54	IP54	IP54	IP67	Indoor Use Only	
Radome Color	White or Black	White	White	Beige	Black or White	White	
Part # Example	PRO4A4L15GW	PTAWM2L15W	PTAWM2W15W	PTAGD2L50	PRO9H4L4WG15B	PRO13BD8L4WG15	
972-804-4600 Sales@Parsec-t.com							



ENTERPRISE C-BAND ANTENNAS

	5G C-Band	C-Band	C-Band	C-Band
Series	 <u>Chinook</u>	 <u>Greyhound</u>	 <u>Pointer</u>	 <u>Chow</u>
Configurable up to:	4 CELL, GPS	4 CELL	4 CELL	2 CELL
Antenna Configuration Options	4:1, 5:1	4:1	4:1	2:1
Compatible Router	4 Cellular	4 Cellular	4 Cellular	2 Cellular
	4 Cellular, 1 GPS			
Cellular Frequency Range	5G & C-Band 600 MHz - 6 GHz	Extended C-Band 1.8 GHz - 4.2 GHz	CBRS 3550-3700 MHz	5G & C-Band 600 MHz - 6 GHz
North American Bands Supported	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71, n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B7, B25, B30, B41, B48, n2, n25, n41, n48, n66, n77	B48, n48	B2, B4, B5, B7, B12, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71, n2, n5, n12, n25, n26, n41, n48, n66, n71, n77
EMEA Bands Supported	B1, B3, B7, B20, B28, B42, B43, B46, n1, n3, n28, n77, n78	B1, B7, B42, B43, n1, n77, n78	N/A	B1, B3, B7, B20, B28, B42, B43, B46, n1, n3, n28, n77, n78
Pattern	Omni-Directional	Directional	Directional	Omni-Directional
IP Rating	Indoor Use Only	Indoor Use Only	Indoor Use Only	IP54
Radome Color	White	White	White	White
Part # Example	PRO4CH4L15W	PRO4GH4JW-NF	PRO4P4C15W	PTA2CW2L15W
972-804-4600 Sales@Parsec-t.com				

MOBILE ANTENNAS

Series	 <i>Belgian Shepherd</i>	 <i>K9</i>	 <i>Australian Shepherd</i>	 <i>Husky</i>	 <i>Irish Setter</i>	 <i>Great Pyrenees</i>
Configurable up to:	4 CELL, 4 WI-FI, GPS	4 CELL, 4 WI-FI, GPS	4 CELL, 4 WI-FI, GPS	4 CELL, 4 WI-FI, GPS	4 CELL, 4 WI-FI, GPS	8 CELL, 4 WI-FI, GPS
Antenna Configuration Options	4:1, 5:1, 7:1, 8:1, 9:1	4:1, 5:1, 7:1, 8:1, 9:1	4:1, 5:1, 7:1, 8:1, 9:1	4:1, 5:1, 7:1, 8:1, 9:1, 11:1	4:1, 5:1, 7:1, 8:1, 9:1	8:1, 9:1, 11:1, 12:1, 13:1
Compatible Router Configurations	4 Cellular	4 Cellular	4 Cellular	4 Cellular	4 Cellular	8 Cellular
	4 Cellular, 1 GPS	4 Cellular, 1 GPS	4 Cellular, 1 GPS	4 Cellular, 1 GPS	4 Cellular, 1 GPS	8 Cellular, 1 GPS
	4 Cellular, 2 Wi-Fi, 1 GPS	4 Cellular, 2 Wi-Fi, 1 GPS	4 Cellular, 2 Wi-Fi, 1 GPS	4 Cellular, 2 Wi-Fi, 1 GPS	4 Cellular, 2 Wi-Fi, 1 GPS	8 Cellular, 2 Wi-Fi, 1 GPS
	4 Cellular, 2 Wi-Fi, 1 Bluetooth, 1 GPS	4 Cellular, 2 Wi-Fi, 1 Bluetooth, 1 GPS	4 Cellular, 2 Wi-Fi, 1 Bluetooth, 1 GPS	4 Cellular, 2 Wi-Fi, 1 Bluetooth, 1 GPS	4 Cellular, 2 Wi-Fi, 1 Bluetooth, 1 GPS	8 Cellular, 2 Wi-Fi, 1 Bluetooth, 1 GPS
Cellular Frequency Range	600 MHz – 6 GHz	600 MHz – 6 GHz	600 MHz – 6 GHz	600 MHz – 6 GHz	600 MHz – 6 GHz	600 MHz – 6 GHz
North American Bands Supported	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77
EMEA Bands Supported	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78
Pattern	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional
IP Rating	IP67	IP67	IP67	IP67	IP67	IP67
Radome Color	Black or White	Black or White	Black or White	Black or White	Black or White	Black or White
Part # Example	PRO9BS4L4WG15B	PRO8K4L2WBG15BS	PTA7AS4L2WG15B	PRO9H4L4WG15B	PRO7IS4L2WG03BS	PRO13GP8L4WG15B



MOBILE ANTENNAS

Series	 <i>Doberman</i>	 <i>Rottweiler</i>	 <i>Border Collie</i>	 <i>German Shepherd</i>
Configurable up to:	2 CELL, 3 WIFI, GPS	2 CELL, 3 WIFI, GPS	2 CELL, 2 WIFI, GPS	2 CELL, 2 WIFI, GPS
Antenna Configuration Options	2:1, 3:1, 5:1, 6:1	2:1, 3:1, 5:1, 6:1	2:1, 3:1, 5:1, 6:1	2:1, 3:1, 5:1
Compatible Router Configurations	2 Cellular	2 Cellular	2 Cellular	2 Cellular
	2 Cellular, 1 GPS	2 Cellular, 1 GPS	2 Cellular, 1 GPS	
	2 Cellular, 2 Wi-Fi, 1 GPS	2 Cellular, 2 Wi-Fi, 1 GPS	2 Cellular, 2 Wi-Fi, 1 GPS	
	2 Cellular, 3 Wi-Fi, 1 GPS	2 Cellular, 3 Wi-Fi, 1 GPS	2 Cellular, 3 Wi-Fi, 1 GPS	
Cellular Frequency Range	600 MHz - 6 GHz	600 MHz - 6 GHz	600 MHz - 6 GHz	600 MHz - 6 GHz
North American Bands Supported	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B48, B66 n2, n5, n12, n25, n26, n41, n48, n66, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77
EMEA Bands Supported	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78	B1, B3, B7, B8, B20, B28, B42, B43 n1, n8, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78
Pattern	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional
IP Rating	IP67	IP67	IP67	IP67
Radome Color	Black or White	Black or White	Black or White	Black or White
Part # Example	PRO5D2L2WG15B	PRO3R2LG15B	PTA5BC2L2WG15B	PRO2GS2L15B

IoT ANTENNAS

Series	 <i>Chihuahua S</i>	 <i>Chihuahua ST</i>	 <i>Chihuahua STX</i>	 <i>Collie</i>	 <i>Falcon</i>	 <i>Thunderbird</i>
Configurable up to:	1 CELL, 1 WIFI, GPS	2 CELL, 3 WIFI, GPS	2 CELL	2 CELL, 2 WIFI, GPS	2 CELL	1 CELL
Antenna Configuration Options	1:1, 2:1, 3:1	2:1, 3:1, 5:1, 6:1	2:1	2:1, 3:1, 5:1	2:1	1:1
Compatible Router Configurations	2 Cellular	2 Cellular	2 Cellular	2 Cellular	2 Cellular	Any SMA Connection
	2 Cellular, 1 GPS	2 Cellular, 1 GPS		2 Cellular, 1 GPS		
	2 Cellular, 2 Wi-Fi, 1 GPS	2 Cellular, 2 Wi-Fi, 1 GPS		2 Cellular, 2 Wi-Fi, 1 GPS		
	2 Cellular, 3 Wi-Fi, 1 GPS	2 Cellular, 3 Wi-Fi, 1 GPS		2 Cellular, 2 Wi-Fi, 1 GPS		
Cellular Frequency Range	698 - 2700 MHz	600 MHz - 6 GHz	698 - 2700 MHz	698 - 3800 MHz	600 MHz - 6 GHz	600 MHz - 6 GHz
North American Bands Supported	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B66	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B30, B41, B66 n2, n5, n12, n25, n26, n41, n66	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B66	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B48, B66 n2, n5, n25, n26, n41, n48, n66, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77
EMEA Bands Supported	B1, B3, B7, B20, B28	B1, B3, B7, B20, B28 n1, n3, n28	B1, B3, B7, B20, B28	B1, B3, B7, B8, B20, B28, B32, B42, B43 n1, n3, n8, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78
Pattern	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional
IP Rating	IP67	IP67	IP67	IP67	IP54	Indoor Only
Radome Color	Black or White	Black or White	Black or White	Black or White	Black	Black
Part # Example	PROISG06B	PRO2ST2L06B	PRO3STX2LG03B	PRO5C2L2WGI5B	PTA2F2L06B	PTATBLB











IoT ANTENNAS

Series	 <i>Red Tailed Hawk</i>	 <i>Albatross</i>	 <i>Boston Terrier</i>	 <i>Pug</i>
Configurable up to:	2 CELL	2 CELL, GPS	2 CELL, 2 Wi-Fi, GPS	2 CELL, 1 WIFI, GPS
Antenna Configuration Options	2:1	2:1, 3:1	2:1, 3:1, 4:1, 5:1	2:1, 3:1, 4:1
Compatible Router Configurations	2 Cellular	2 Cellular	2 Cellular 2 Cellular, 1 GPS	2 Cellular
		2 Cellular, 1 GPS	2 Cellular, 2 Wi-Fi, 1 GPS	2 Cellular, 1 GPS
Cellular Frequency Range	600 MHz - 6 GHz	600 MHz - 6 GHz	600 MHz - 6 GHz	600 MHz - 6 GHz
North American Bands Supported	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	Coming Soon	Coming Soon	Coming Soon
EMEA Bands Supported	B1, B3, B7, B20, B28, B42, B43, B46 n1, n3, n28, n77, n78	Coming Soon	Coming Soon	Coming Soon
Pattern	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional
IP Rating	IP54	IP54	IP67	IP67
Radome Color	Black	Black or White	Black	Black
Part # Example	PTA2RH2L15B	PTA3AB2LG10W	PRO5BT2L2WG15B	PRO4PG2LWG06B

972-804-4600 | Sales@Parsec-t.com

5G ANTENNAS

Series	 <i>Doberman</i>	 <i>Rottweiler</i>	 <i>Belgian Shepherd</i>	 <i>K9</i>	 <i>Border Collie</i>	 <i>Australian Shepherd</i>	 <i>Husky</i>	 <i>German Shepherd</i>	 <i>Bulldog</i>	 <i>Akita</i>	 <i>Labrador</i>	 <i>Chinook</i>	 <i>Irish Setter</i>	 <i>Great Pyrenees</i>	
Configurable up to:	2 CELL, 3 WIFI, GPS	2 CELL, 3 WIFI, GPS	4 CELL, 4 WI-FI, GPS	4 CELL, 4 WI-FI, GPS	2 CELL, 2 WIFI, GPS	4 CELL, 4 WI-FI, GPS	4 CELL, 4 WI-FI, GPS	2 CELL, 2 WIFI, GPS	8 CELL, 4 WI-FI	4 CELL, 1 GPS	2 CELL	4 CELL, GPS	4 CELL, 4 WI-FI, GPS	8 CELL, 4 WI-FI, GPS	
Antenna Configuration Options	2i, 3i, 5i, 6i	2i, 3i, 5i, 6i	4i, 5i, 7i, 8i, 9i	4i, 5i, 7i, 8i, 9i	2i, 3i, 5i, 6i	4i, 5i, 7i, 8i, 9i	4i, 5i, 7i, 8i, 9i, 11i	2i, 3i, 5i	4i, 8i, 12i	4i, 5i	2i	4i, 5i	4i, 5i, 7i, 8i, 9i	8i, 9i, 11i, 12i, 13i, 1	
Compatible Router Configurations	2 Cellular	2 Cellular	4 Cellular	4 Cellular	2 Cellular	4 Cellular	4 Cellular	2 Cellular	4 Cellular	4 Cellular	2 Cellular	4 Cellular	4 Cellular	8 Cellular	
	2 Cellular, 1 GPS	2 Cellular, 1 GPS	4 Cellular, 1 GPS	4 Cellular, 1 GPS	2 Cellular, 1 GPS	4 Cellular, 1 GPS	4 Cellular, 1 GPS		4 Cellular, 4 WI-FI			4 Cellular	4 Cellular, 1 GPS	4 Cellular	4 Cellular, 1 GPS
Cellular Frequency Range	2 Cellular, 2 WI-FI, 1 GPS	2 Cellular, 2 WI-FI, 1 GPS	4 Cellular, 2 WI-FI, 1 GPS	4 Cellular, 2 WI-FI, 1 GPS	2 Cellular, 2 WI-FI, 1 GPS	4 Cellular, 2 WI-FI, 1 GPS	4 Cellular, 2 WI-FI, 1 GPS	2 Cellular, 1 GPS	8 Cellular, 4 WI-FI	4 Cellular, 1 GPS	2 Cellular	4 Cellular, 1 GPS	4 Cellular, 2 WI-FI, 1 GPS	8 Cellular, 2 WI-FI, 1 GPS	
	2 Cellular, 3 WI-FI, 1 GPS	2 Cellular, 3 WI-FI, 1 GPS	4 Cellular, 3 WI-FI, 1 Bluetooth, 1 GPS	4 Cellular, 2 WI-FI, 1 Bluetooth, 1 GPS	2 Cellular, 3 WI-FI, 1 GPS	4 Cellular, 2 WI-FI, 1 Bluetooth, 1 GPS	4 Cellular, 2 WI-FI, 1 Bluetooth, 1 GPS	2 Cellular, 2 WI-FI, 1 GPS	8 Cellular, 4 WI-FI	4 Cellular, 1 GPS		4 Cellular, 1 GPS	4 Cellular, 1 GPS	4 Cellular, 2 WI-FI, 1 Bluetooth, 1 GPS	8 Cellular, 2 WI-FI, 1 Bluetooth, 1 GPS
North American Bands Supported	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	82, 84, 85, 87, 812, 813, 814, 817, 825, 826, 829, 830, 841, 846, 848, 866, 871 n2, n5, n12, n25, n26, n41, n48, n66, n71, n77
EMEA Bands Supported	81, 83, 87, 820, 828, 842, 843, 846 n1, n3, n28, n77, n78	81, 83, 87, 88, 820, 828, 842, 843 n1, n8, n28, n77, n78	81, 83, 87, 820, 828, 842, 843, 846 n1, n3, n28, n77, n78	81, 83, 87, 820, 828, 842, 843, 846 n1, n3, n28, n77, n78	81, 83, 87, 820, 828, 842, 843, 846 n1, n3, n28, n77, n78	81, 83, 87, 820, 828, 842, 843, 846 n1, n3, n28, n77, n78	81, 83, 87, 820, 828, 842, 843, 846 n1, n3, n28, n77, n78	81, 83, 87, 820, 828, 842, 843, 846 n1, n3, n28, n77, n78	81, 83, 87, 820, 828, 842, 843, 846 n1, n3, n28, n77, n78	81, 83, 87, 88, 820, 828, 832, 842, 843, 846 n1, n3, n8, n28, n77, n78	81, 83, 87, 820, 828, 842, 843, 846 n1, n3, n8, n28, n77, n78	81, 83, 87, 820, 828, 842, 843, 846 n1, n3, n28, n77, n78	81, 83, 87, 820, 828, 842, 843, 846 n1, n3, n28, n77, n78	81, 83, 87, 820, 828, 842, 843, 846 n1, n3, n28, n77, n78	
Pattern	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	
IP Rating	IP67	IP67	IP67	IP67	IP67	IP67	IP67	IP67	Indoor Use Only	IP54	IP54	Indoor Use Only	IP67	IP67	
Radome Color	Black or White	Black or White	Black or White	Black or White	Black or White	Black or White	Black or White	Black or White	White	White or Black	White	White	Black or White	Black or White	
Part # Example	PRO5D2L2WG15B	PRO3R2L1G15B	PRO9BS4L4WG15B	PRO8K4L2WBG15B	PTA5BC2L2WG15B	PTA7A54L2WG15B	PRO9H4L4WG15B	PRO2GS2L15B	PRO12B08L4W15	PRO4A4L15GW	PTAWM2L15W	PRO4CH4L15W	PRO7S4L2W0038S	PRO13GP8L4WG15B	



CASE ANTENNAS

Series	 <i>Golden Retriever</i>	 <i>Beagle</i>	 <i>Boxer</i>	 <i>St. Bernard</i>	 <i>Bernese Mountain Dog</i>	 <i>Bloodhound</i>	 <i>Newfoundland</i>
Configurable up to:	2 CELL, 2 WIFI, GPS	2 CELL, 3 WIFI, GPS	4 CELL, 4 WIFI, GPS	4 CELL, 4 WIFI, GPS	6 CELL, 2 WIFI, GPS	8 CELL, 4 WIFI, GPS	8 CELL, 4 WIFI, GPS
Antenna Configuration Options	5:1	5:1, 6:1	9:1	9:1	7:1, 8:1, 9:1	7:1, 8:1, 9:1, 13:1	5:1, 13:1
Compatible Router Configurations	2 Cellular, 2 Wi-Fi, 1 GPS	2 Cellular, 2 Wi-Fi, 1 GPS	4 Cellular, 4 Wi-Fi, GPS	4 Cellular, 4 Wi-Fi, 1 GPS	4 Cellular, 2 Wi-Fi, 1 GPS	4 Cellular, 2 Wi-Fi, 1 GPS	4 Cellular, 2 Wi-Fi, 1 GPS
		2 Cellular, 3 Wi-Fi, 1 GPS			4 Cellular, 2 Wi-Fi, 1 Bluetooth, 1 GPS	4 Cellular, 2 Wi-Fi, 1 Bluetooth, 1 GPS	4 Cellular, 4 Wi-Fi, GPS
Cellular Frequency Range	600 MHz - 3.8 GHz	600 MHz - 6 GHz	600 MHz - 6 GHz	600 MHz - 6 GHz	600 MHz - 6 GHz	600 MHz - 6 GHz	600 MHz - 6 GHz
North American Bands Supported	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B66	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, n2, n5, n12, n25, n26, n41, n48, n66, n77	B1, B3, B7, B20, B28, B42, B43, B46, n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71, n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71, n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71, n2, n5, n12, n25, n26, n41, n48, n66, n71, n77	B2, B4, B5, B7, B12, B13, B14, B17, B25, B26, B29, B30, B41, B46, B48, B66, B71, n2, n5, n12, n25, n26, n41, n48, n66, n71, n77
EMEA Bands Supported	B1, B3, B7, B20, B28	B1, B3, B7, B8, B20, B28, B42, B43, B46, n1, n3, n8, n28, n77, n78	B1, B3, B7, B8, B20, B28, B42, B43, B46, n1, n3, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46, n1, n3, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46, n1, n3, n28, n77, n78	B1, B3, B7, B20, B28, B42, B43, B46, n1, n3, n28, n77, n78	B1, B3, B7, B8, B20, B28, B42, B43, B46, n1, n3, n8, n28, n77, n78
Pattern	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional	Omni-Directional
IP Rating	IP67	IP67	IP67	IP67	IP67	IP67	IP67
Case Accessories	1x USB Adapter, 2x RJ-45, Router Mount Plate, Battery Tray, Top Cover, USB Adapter, USB C-Charging Port, 1x Fan	1x USB Adapter, 2x RJ-45, Battery Tray, Fan, Barrel Connector, ChargeTech Battery	1x USB-C, 2x RJ-45, Battery Tray, Fan	1x USB Adapter, 4x RJ-45, Router Mount Plate, Battery Tray, Top Cover, Barrel Connector, Fan and Vent	1x USB, 4x RJ-45, Battery Tray, Router Mount Plate, Top Cover, Barrel Connector, Fan	1x USB, 4x RJ-45, 54 Battery Tray, Fan and Vent, Barrel Connector, Router Mount Plate, Top Cover	1x USB Adapter, 4x RJ-45, Router Mount Plate, AC Adapter, Barrel Connector, Fan and Vent, Top Cover, Battery Tray
Part # Example	PRO5GR2L2WG	PRO6B2L3WG	PRO9BX4L4WG	PRO9SB4L4WG	PRO9MD6L2WG	PRO13BH8L4WG	PRO13N8L4WG

872-804-4800 | Sales@Parsec-t.com